

**Amendments to the Claims:**

This listing of claims will replace all prior versions, and listings, of claims in the application.

**Listing of the Claims**

Claims 1 - 16 (cancelled)

Claim 17 (currently amended) A device for contactless electrical power transmission in a rotary-wing aircraft system including ~~aat least one~~ stationary portion of a rotor shaft bearing of a rotary-wing aircraft and a rotor shaft of the rotary-wing aircraft~~one moving part~~, power being transmitted between the ~~at least one stationary~~ portion of the rotor shaft bearing of the rotary-wing aircraft ~~[[part]]~~ and the rotor shaft of the rotary-wing aircraft~~at least one moving part~~, the device comprising:

an inductive transformer including a primary winding disposed on the stationary portion of the rotor shaft bearing of the rotary-wing aircraft ~~[[part]]~~ and a secondary winding disposed on the rotor shaft of the rotary-wing aircraft~~moving part~~, the inductive transformer bridging an isolating point between the stationary portion of the rotor shaft bearing of the rotary-wing aircraft ~~[[part]]~~ and the rotor shaft of the rotary-wing aircraft~~moving part~~;

a frequency generator having a series-resonant circuit capacitor connected to the primary winding; and

at least one actuator control element connected to the secondary winding and including a matrix arrangement of a plurality of switchable power semiconductors, wherein at least portions of the inductive transformer, frequency generator and at least one actuator control element are disposed in an area of the~~the~~ ~~[[a]]~~ rotor shaft and a rotor head of the~~the~~ ~~[[a]]~~ rotary-wing aircraft.

Claim 18 (previously presented) The device as recited in claim 17, further comprising at least one capacitive actuator disposed in operative connection with the at least one actuator control element.

Claim 20 (currently amended) The device as recited in claim 17, wherein:

b) the unipolar switchable power semiconductors are disposed in direction relative to the only one polarity of the output voltage and are configured to take up the output voltage as blockage voltage and to switch ~~[[off]]~~ the current from a positive one of ~~[[the]]~~ at least one ~~positive~~ output conductor to an alternating current input.

Claim 22 (currently amended) The device as recited in claim 18, wherein:

the regulator is connected to the controller so as to control the power semiconductors using a polarity signal as a function of a polarity sign of the difference between the setpoint actuator voltage and the actual actuator voltage, in such a way that, when the polarity sign of the difference is negative, a successive charge or power is withdrawn from the actuator from one

half-wave to the next and, when the polarity sign of the difference is positive, a successive charge or power is supplied to the actuator from one half-wave to a[[the]] next half-wave.

Claim 23 (currently amended) The device as recited in claim 22, wherein:

a) the actuator control element includes a plurality of generating devices and the controller for impressing half-waves or half-wave segments of the alternating current into the actuator is connected to the generating devices so as to generate switching grid signals of a switching grid synchronized with the alternating current;

b) the controller includes a logic device configured to form ~~conductive-area~~ switching signals of an initial position of pairs of the switchable semiconductors connected in series using the switching grid signals;

c) the controller includes a shift advance device configured to advance ~~switchinga shift of~~ switchinga shift of ~~conductive areas~~ of a switch pair by a shift relative to the initial position during a rectifier operation and the controller includes a shift ~~lag~~ lag device configured to subtract ~~switchinga shift of the conductive areas~~ switchinga shift of the conductive areas of the switch pair by the shift relative to the initial position during an inverter operation; and

d) the controller is connected to the regulator so as to supply the polarity signal so as to set a direction of the shift and a[[the]] magnitude signal so as to set a[[the]] magnitude of the shift.

Claim 24 (cancelled)

Claim 25 (currently amended) The device as recited in claim 17 ~~[[24]]~~, further comprising an azimuth sensor disposed on the rotor shaft and having an output connected to the actuator control element.

Claim 26 (currently amended) The device as recited in claim 17, further comprising:

an aerodynamically ~~active~~ effective device actuated by a[[the]] capacitive actuator and having an output connected to the capacitive actuator; and

at least one sensor disposed in an area of a[[the]] rotor blade and configured to detect a position of the aerodynamically effective device.

Claim 27 (previously presented) The device as recited in claim 17, further comprising electrical controls and wherein the actuator control element and the electrical controls are disposed in the rotor head and are connected to the inductive transformer via lines disposed in the rotor shaft.

Claim 28 (currently amended) A method to provide power of at least one capacitive actuator wherein the at least one actuator is arranged on a moving part system that is separated from a stationary system by an isolating point, the method comprising:

generating a high[[er]]-frequency alternating current from a direct voltage using a frequency generator disposed in the stationary system, the high[[er]]-frequency alternating current having an amplitude independent of a phase angle and of an amplitude of a reverse voltage;

transmitting the alternating current from a primary winding of an inductive transformer that bridges the isolating point; and

separating the alternating current coming from a secondary winding of the inductive transformer in the moving part system into positive and negative half-waves or segments of these half-waves and always impressing the alternating current into the at least one actuator using an electronic control element in a direction such that a length change of the actuator occurs in a desired direction in each half-wave.

Claim 29 (currently amended) A method to provide power of at least one capacitive actuator, the method comprising:

generating a high[[er]]-frequency alternating current from a direct voltage using a frequency generator, the high[[er]]-frequency alternating current having an amplitude independent of a phase angle and of an amplitude of a reverse voltage;

separating the high[[er]]-frequency alternating current into positive and negative half-waves or segments of these half-waves;

always impressing the high[[er]]-frequency alternating current into the actuator using an electronic control element in such a direction that a length change of the actuator occurs in a desired direction in each half-wave.